



How to... Configure OT/PPP - all GV Modems

Introduction:

This document provides general information about how to configure OT/PPP for your Global Village modem. For detailed information about using OT/PPP software, refer to the documentation provided with OT/PPP. Due to the nature of its older technology, Global Village Bronze/Bronze II modems are not supported with OT/PPP.

To configure OT/PPP for all Global Village modems, follow the instructions below:

1. Open your **TCP/IP** control panel. Click on the **Connect via** pop-up menu and select **PPP**.
2. Open your **PPP** or **Remote Access** (for ARA 3.0 which comes with OS 8.5) control panel and type in your name, password, and dial-up number.

NOTE: If you are unsure of your name, password and dial-up number you will need to contact your Internet Service Provide (ISP) for assistance.

3. Open your **Modem** control panel. Click on the **Connect via** pop-up menu and select the appropriate port for your modem.
4. Click on the **Modem** pop-up menu and select the appropriate script for your modem.

NOTE: If you can not find the appropriate script for your modem or your modem has problems connecting to your ISP using the script that you configured for OT/PPP then read the section of this document titled **Downloading Current Scripts**.

Downloading Current Scripts

If you have problems using the script that you first configured for OT/PPP you will need to ensure that you're using the latest modem script for your modem.

1. Log on to our website at: <http://www.globalvillage.com/support/scriptlocator.html>, find your modem model and download the appropriate script for your modem.

2. Open your **Modem Scripts** folder, located in your **System Folder** in your **Extensions** folder. Place the script that you downloaded into the Modem Scripts folder.
3. Open your **Modem** control panel. Click on the **Connect via** pop-up menu and select the appropriate port for your modem.
4. Click on the **Modem** pop-up menu and select the script that you downloaded and installed.